



## Asanté's 8-port 10Mbps Switches with two 10/100 Ports Deliver a High-performance, Plug-and-play Solution for Desktops and Servers

### FriendlyNet 8+2 Switches



#### Integrating FriendlyNet 8+2 Switches with Your Network

- With FriendlyNet™ 8+2 switches users and network administrators can combat congestion with direct connections to high-bandwidth users, fast workgroup servers, or network backbones.
- FriendlyNet's plug-and-play design easily integrates your present networking structure without the purchase of additional equipment.

#### Performance and Flexibility

- FriendlyNet 8+2 switches are available in two variations; the FriendlyNet FS3208 is designed for the smaller network supporting up to 32 total network users, and the FriendlyNet FS3208Plus is designed for the larger network or workgroup supporting up to 3000 total network users.
- Both the FriendlyNet FS3208 and the FS3208Plus are designed with eight 10Mbps ports with two 10/100Mbps ports that support network speeds up to 100Mbps full-duplex operation—delivering high-speed connectivity to corporate networks, power users and high-speed servers.
- NWay auto-negotiation on the two 10/100 ports makes configuration of your network devices easy. This dynamic feature automatically detects and configures 10 or 100Mbps operation to insure you are achieving optimum speed.
- FriendlyNet 8+2 also provides the flexibility of one dedicated (RJ-45) uplink port, allowing connection to a backbone or to another switch without a crossover cable. (Note this is not an additional switched port.)

#### Plug-and-play Design

#### Easy Set-up and Visual Management

- The plug-and-play design of Asanté's FriendlyNet switches make set-up and connection to your PCs, Macintoshes, servers and workstations easy—to get you up and running in no time.
- Easy to read LED lights provide at-a-glance management displaying link status, port activity, collision status, 10/100Mbps, and full-duplex operation, for simple network diagnostics.

#### Free Technical Support

#### Technical Support

- Asanté offers free technical support by calling our toll-free technical support line at (800) 566-6680 from 7 AM - 6 PM (MST) Monday through Friday, via Email, our Web site, or our 24-hour BBS.

#### Limited Lifetime Warranty

#### Warranty

- Asanté stands behind the reliability of FriendlyNet 8+2 switches by providing a Limited Lifetime Warranty, without the purchase of an extended warranty contract.

#### FriendlyNet 8+2 Switches Add Up to Value

- FriendlyNet provides accelerated network performance, delivering more power to your desktop, and combines it with cost-effective pricing, free technical support, and Asanté's Limited Lifetime Warranty. While the performance, affordability, free support, and warranty alone, make FriendlyNet a true value—combined with FriendlyNet's plug-and-play design for hassle-free set-up, there is no reason not to switch.

Limited Lifetime  
Warranty  
Asanté stands behind  
FriendlyNet 8+2  
switches by providing a  
Limited Lifetime  
Warranty.

Free Technical Support  
Asanté provides free  
telephone support  
7AM to 6PM (MST)  
as well as 24-hour  
BBS and World Wide  
Web support.

## SPECIFICATIONS

<b>LEDs:</b>	Power, link, data, collision, maximum utilization, full-duplex and 10/100Mbps operation
<b>Connector:</b>	RJ-45 (10Base-T and 100Base-TX)
<b>Switching Method:</b>	Store-and-forward
<b>Buffer Size:</b>	
FS3208 switch:	1 MB
FS3208 <i>Plus</i> switch:	4 MB
<b>MAC Address Table Size:</b>	
FS3208 switch:	32
FS3208 <i>Plus</i> switch:	3000
<b>Dimensions:</b>	11" x 6.7" x 1.8" (279 x 170 x 46 mm) 1 RU high
<b>Weight:</b>	7 lbs (3.18 kg)
<b>Accessories Included:</b>	
FS3208 switch:	Wall-mount kit, external power adapter
FS3208 <i>Plus</i> switch:	Wall-mount kit, 19" rack mount brackets with screws and external power adapter
<b>Power Requirements:</b>	
Voltage Range:	12 Vdc, 1.5 A
<b>Environmental Operating Range:</b>	
Operating Temperature:	0° to 40° C
Relative Humidity:	5% to 85% non-condensing
<b>Standards Compliance:</b>	IEEE 802.3, and 802.3u Ethernet Specifications
Emissions:	FCC Class A, CE
<b>Support:</b>	Limited Lifetime Warranty • Free Technical Support • World Wide Web • 24-hour Commercial Online BBS

## ORDERING INFORMATION

Name	Description	Asanté Part # *
FriendlyNet FS3208 Switch	Eight 10/100Mbps ports and two NWay auto-negotiation ports (RJ-45) with one (RJ-45)10/100 uplink port, supports up to 32 MAC addresses	99-00467-81
FriendlyNet FS3208 <i>Plus</i> Switch	Eight 10/100Mbps ports and two NWay auto-negotiation ports (RJ-45) with one (RJ-45)10/100 uplink port, supports up to 3000 MAC addresses	99-00443-81
Rack-mount Kit	Optional for FS3208 Switch	99-00469-81

\* For international specific part numbers, please refer to the Asanté price list.

Asanté Technologies, Inc. • 821 Fox Lane, San Jose, CA 95131 U.S.A. • T: 408.435.8388, 800.662.9686 F: 408.432.7511;  
Asanté-Asia T: 886.22.546.1515 F: 886.22.546.1516;  
Asanté-Europe T: 44(0)1985.846.300 F: 44(0)1985.846.600  
Sales Email: sales@asante.com • Tech Support Email: support@asante.com • Web Site: www.asante.com • Asanté-NASDAQ: ASNT.  
Copyright©1998 Asanté Technologies, Inc. All brand names and products are trademarks or registered trademarks of their respective holders.  
All features and specifications subject to change without notice.  
06-00413-00.11/98



Free telephone support and 24-hour BBS.  
Call our support line at (800) 566-6680 or visit [www.asante.com](http://www.asante.com) for more information.